

INSTALLATION & MAINTENANCE INSTRUCTIONS FOR THE CYLINDER SCONCES

Wall Mounted Luminaire


TERON
Lighting, Inc.
Innovative, Efficient Luminaires

Echelon
COLLECTION **TERON**
SERIES


76034

INSTALLATION


NOTE: THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.




Aztec



Emerald



Landmark



Gemini

- 1] The Cylinder Sconces are designed to be mounted directly to a 4" sq junction box, using a nipple and crossbar.
- 2] Attach the crossbar (See detail) to the J-box, and install the nipple in position. Slip the mount pan over the nipple, and secure to the wall with the brass cap included in the mount kit. Be sure to align the fixture on the wall properly.
- 3] Connect the fixture leads to the supply leads. Teron stipulates the Black as Line; White as Common; Bare as Ground.
- 4] See the listing below for directions to attach the lens to the mount pan.
- 5] Check the re-lamp label to ensure that the lamp is the specified wattage. Fluorescent lamps will not snap into incorrect lampholders.

ATTACHING LENS

Aztec - The lens is held in place by trim and (2) decorative caps.

Emerald - The lens and trim are held in place by (2) screws.

Landmark - The lens slides into place from the top of the fixture.

Gemini - The lens slides into place from the top of the fixture.



Crossbar

MAINTENANCE

The lens should be cleaned once every 6 months. The lens panels must be washed in a mild soap solution. DO NOT use cleansers containing bleach.

The metal portion of the fixture can be wiped clean as needed using a mild soap solution.

ATTENTION: Avoid moving any exposed wires. If any wires are accidentally disconnected, call a professional to repair.

These instructions are general to the fixture noted.
Due to the numerous options, all variations may
not be covered.

Installation of an electrical luminaire must be
performed by a qualified professional. The
fixture must be wired in accordance to all
local & national electrical codes.